

Applicant : Gerhard Nossing
Serial No. :
Filed : December 7, 2001
Page : 7

Attorney's Docket 12816-036001 / S1139 GC/rfu

REMARKS

The specification has been amended to cancel claims 1-16 and claims 17-44 have been added.

Attached is a marked-up version of the changes being made by the current amendment.

Applicant asks that all claims be examined. Please apply any other charges or credits to Deposit Account No. 06-1050.

Respectfully submitted,

Date: December 7, 2001

Ellen Sein Aye
Ellen Sein Aye
Reg. No. 42,729

Fish & Richardson P.C.
225 Franklin Street
Boston, Massachusetts 02110-2804
Telephone: (617) 542-5070
Facsimile: (617) 542-8906

20355597.doc

20355597.doc

10/009747

581 Rec'd PCT/PT 07 DEC 2001

Version with markings to show changes made

In the claims:

Claims 1-16 have been cancelled.

Claims 17-44 have been added:

-- 17. A circuit for interference-proof detection in the operation of a grounding key, the circuit comprising:

a current detection device configured to detect a current flowing when the grounding key is in operation;

a comparator configured to compare the detected current with at least one threshold value; and

a monitoring circuit configured to:

detect a first period when the current exceeds the threshold value;

detect a second period when the current drops below the threshold value;

and

output a grounding key detection signal when the first period is greater than the second period.

18. The circuit of claim 17 wherein the comparator includes:

a first comparator circuit configured to compare the detected current with an upper threshold value; and

a second comparator circuit configured to compare the detected current with a lower threshold value.

19. The circuit of claim 18 wherein the monitoring circuit is configured to output the grounding key detection signal when the first period of the current at the first comparator circuit is greater than the second period.

201710-24260001

20. The circuit of claim 18 wherein the monitoring circuit is configured to output the grounding key detection signal when the second period of the current at the second comparator circuit is greater than the first period.

21. The circuit of claim 17 wherein the monitoring circuit includes at least one internal counter configured to count up when the upper threshold value has been exceeded by the current and at least one internal counter configured to count down when the lower threshold value has not been exceeded by the current.

22. The circuit of claim 21 wherein the monitoring circuit includes at least one internal counter configured to count up when the lower threshold value has not been exceeded by the current and at least one internal counter configured to count down when the lower threshold value has been exceeded by the current.

23. The circuit of claim 22 wherein the internal counter is configured to perform a counting process for a predetermined period.

24. The circuit of claim 23 wherein the counting period is adjustable and configured to correspond to at least half of a period of an interference signal having a maximum interference frequency.

25. The circuit of claim 23 wherein the counting period is adjustable and configured to correspond to at least half of a period of an interference signal having a minimum interference frequency.

26. The circuit of claim 25 wherein the minimum interference frequency of the interference signal is a frequency from a group consisting of $16 \frac{2}{3}$ Hertz (Hz), 50Hz, 60Hz, or 120 Hz.

2014-07-24 10:00:00

27. The circuit of claim 18 wherein the upper threshold value is positive 17 milli-Amperes (mA) and the lower threshold value is negative 17 mA.

28. The circuit of claim 17 wherein the monitoring circuit includes a polarity detection device configured to detect a polarity of the current.

29. The circuit of claim 28 wherein an internal counter of the polarity detection device is configured to count a number of polarity changes of the current.

30. The circuit of claim 29 wherein if a predetermined adjustable threshold count is exceeded, the polarity detection device is configured to output an external alternating current signal.

31. The circuit of claim 1 wherein the monitoring signal is configured to output the grounding key detection signal after a predetermined adjustable period has elapsed.

32. The circuit of claim 31 wherein the predetermined adjustable period is 4 milliseconds (ms).

33. The circuit of claim 31 wherein an internal counter of the monitoring circuit detects a lapse of the predetermined adjustable period.

34. The circuit of claim 1 wherein the current detection device is an integrated circuit for digital telephone switching.

35. A method for interference-proof detection in the operation of a grounding key, the method comprising:

detecting a current flowing when the grounding key is in operation;
comparing the detected current with at least one threshold value;

10009747-041102

detecting a first period during which the current exceeds the threshold value and
detecting a second period during which the current drops below the threshold value; and
outputting a grounding key detection signal when the first period is greater than
the second period.

36. The method of claim 35 further comprising outputting the grounding key
detection signal when the first period is greater than the second period and a predetermined
adjustable period has elapsed.

37. The method of claim 35 further comprising:
comparing the detected current with an upper threshold value; and
comparing the detected current with a lower threshold value.

38. The method of claim 37 further comprising outputting the grounding key
detection signal when the first period of the current at the first comparator circuit is greater than
the second period.

39. The method of claim 37 further comprising outputting the grounding key
detection signal when the second period of the current at the second comparator circuit is greater
than the first period.

40. The method of claim 37 further comprising counting up when the upper threshold
value has been exceeded by the current and counting down when the lower threshold value has
not been exceeded by the current.

41. The method of claim 37 further comprising counting up when the lower threshold
value has not been exceeded by the current and counting down when the lower threshold value
has been exceeded by the current.

2011-10-24 10:47:47

Applicant : Gerhard Nossing
Serial No. :
Filed : December 7, 2001
Page : 12

Attorney's Docket : 12816-036001 / S1139 GC/rfu

42. The method of claim 37 further comprising counting processes for a predetermined period.

43. The method of claim 42 further comprising adjusting the predetermined period to correspond to at least half of a period of an interference signal having a maximum interference frequency.

44. The method of claim 42 further comprising adjusting the counting period to correspond to at least half of a period of an interference signal having a minimum interference frequency. --

In the abstract:

Replace the abstract with the following version.

-- A grounding key detecting device and method for interference-proof detection of the operation of grounding keys in telephones. A circuit that detects the operation of a grounding key includes a current detection device configured to detect a current flowing when the grounding key is in operation, a comparator configured to compare the detected current with at least one threshold value, and a monitoring circuit configured to detect a first period when the current exceeds the threshold value, detect a second period when the current drops below the threshold value, and output a grounding key detection signal when the first period is greater than the second period. --

2011-12-07 10:44:47